

MÜLLER-LICHT International GmbH - IR-Codes (HEX) LED Accessoires

Stick/Strip/Downlight analog

| | | | |
|---------------|---------------|---------------|---------------|
| + | - | Off☒ | On |
| F700FF | F7807F | F7C0BF | F7C03F |
| R | G | B | W |
| F720DF | F7A05F | F7609F | F7E01F |
| R1 | G1 | B1 | Flash |
| F710EF | F7906F | F750AF | F7D02F |
| R2 | G2 | B2 | Strobe |
| F730CF | F7B04F | F7708F | F7F00F |
| R3 | G3 | B3 | Fade |
| F708F7 | F78877 | F748B7 | F7C837 |
| R4 | G4 | B4 | Smooth |
| F728D7 | F7A857 | F76897 | F7E817 |



LED-Strip digital

| | | | |
|---------------|---------------|---------------|---------------|
| + | - | W/WW | On/Off |
| F700FF | F7807F | F740BF | F7C03F |
| IC Set | < > | > < | Auto |
| F720DF | F7A05F | F7609F | F7E01F |
| CS | << | >> | o |
| F710EF | F7906F | F750AF | F7D02F |
| C3 | <+ | +> | Flash |
| F730CF | F7B04F | F7708F | F7F00F |
| C7 | <- | -> | Jump |
| F708F7 | F78877 | F748B7 | F7C837 |
| C16 | o- | -o | Meteor |
| F728D7 | F7A857 | F76897 | F7E817 |



Birne/Downlight/Kugel/Zylinder

On/Off W Auto Color
807F38C7 807FB847 807F7887

Color1 Color2 Color3
807F18E7 807F9867 807F58A7

Color 4 Color5
807FA05F 807F609F

R G B
807F10EF 807F906F 807F50AF

Y C M
807F10EF 807F906F 807F50AF

-- - 0 + ++
807F00FF 807F807F 807F40BF 807FC03F 807FE817



LED-Birne A60 alt

Off On
1FE48B7 1FE7887

R G B
FF906F FF10EF FFD02F

Y C M
1FEE01F 1FE10EF 1FE906F

- +
1FE50AF 1FEF807

Auto White manually
1FE30CF 1FEB04F 1FE708F



iDual LED (0x407F + Code)

| | | | |
|---------------------------------|-------------------------------|---------------------------------|----------------------------------|
| | | | On 807F |
| - | | + | Off |
| 08F7 | | 906F | 40BF |
| Candle 2200K 8877 | ww 2700K 6897 | neutral 4000K 50AF | Daylight 6500K C03F |
| Night 48B7 | Sleep 30min E817 | Work D02F | Relax 20DF |
| Wake up 20min C837 | Pastel 18E7 | Party 30CF | Sunset A05F |
| Forest 28D7 | Water 9867 | Fire B04F | Romance 609F |
| | | Red 708F | |
| Blue A857 | FullColor 58A7 | Pastel F00F | Yellow E01F |
| | | Green 10EF | |



LED-Strip analog 2014 ALT

| | | | |
|---------------|---------------|---------------|---------------|
| + | - | Off☒ | On |
| FFA05F | FF20DF | FF609F | FFE01F |
| R | G | B | W |
| FF906F | FF10EF | FF50AF | FFD02F |
| R1 | G1 | B1 | Flash |
| FFB04F | FF30CF | FF708F | FFF00F |
| R2 | G2 | B2 | Strobe |
| FFA857 | FF28D7 | FF6897 | FFE817 |
| R3 | G3 | B3 | Fade |
| FF9867 | FF18E7 | FF58A7 | FFD827 |
| R4 | G4 | B4 | Smooth |
| FF8877 | FF08F7 | FF48B7 | FFC837 |

